



FRONT
INPUTS

OWNER'S MANUAL

YCP-AS AUTOMATIC AUDIO & VIDEO SWITCHER



BACK
OUTPUTS

Y/C PLUS, INC.® introduces a new *switch* to the old way of switching video and audio. The YCP-AS delivers an inexpensive solution for automatic video switching with audio follow. The concept is simple, the YCP-AS will switch both video and audio to the "B" channel whenever a video input is detected. This allows applications such as, FYI Cable Channels or In-House Communications Channels to insert video tape programs without requiring an on-site operator. When video is no longer detected on the "B" channel the YCP-AS routes the video and audio back to the "A" channel.

When the primary video source is connected to the "B" channel, the YCP-AS can be used as a monitor for satellite downlinks or VCR's when a loss of signal occurs. The "A" channel can be used as a standby video and audio source.

The YCP-AS also offers a dry contact closure for alarm systems, such as, a dialer for pagers or buzzers. An internal switch allows for the alarm to activate either on the "A" or "B" channels. A 3-pin plug is supplied.

The LED will light when the unit has switched to the alternate channel.

The YCP-AS has two BNC composite video and two RCA Stereo audio 10K Ω unbalanced inputs. The outputs are one BNC composite video and two audio stereo 10K Ω unbalanced and one contact closure.

The YCP-AS is supplied with a 5V AC power supply and three pin modular plug for alarm interfacing. Use only power supply shipped with the YCP-AS. Failure to do so can cause serious damage to the unit and injury to the user. If your power supply fails contact your dealer for a replacement.

310 SW 6TH AVE, TOPEKA, KS 66603-3109 USA
785-235-5014 FAX 785-235-3485
www.ycplus.com